



DESCRIPTION

The **CBS ArcSafe® RSA-154F** allows technicians to remotely close or open the Siemens Vacu-Break fusible panel unit switches from a safe distance while remaining stationed outside of the arc-flash boundary. Installation and operation does not require any modifications to the existing electrical equipment. The RSA-154F is compatible with all type VF357, VB357, VF358, and VB358 Siemens Vacu-Break panel switches with a 25" height and ratings from 800-1200A. Typical applications of these switches include manufacturing plants, mass-production industries, and commercial, institutional, and other large buildings served by network systems or transformers of higher capacities. The RSA-154F is a cost-effective solution for keeping operators safe when compared to other arc-flash mitigation alternatives.

SPECIFICATIONS

| | |
|-----------------------|--|
| WEIGHT: | 25 lbs |
| DIMENSIONS: | 9"H x 25.5"W x 10"D |
| POWER CONSUMPTION: | 100W |
| OPERATING DISTANCE: | 25-300 feet |
| COMPATIBILITY: | Siemens Vacu-Break Fusible Panel Units Main Switches VF357, VB357, VF358, VB358 (Suffix TL or BL; 800-1200A; 25" Height) |
| CONTROL/POWER SOURCE: | CBS ArcSafe® RSO-I AR Control Console |

OVERVIEW

- Remote operation from up to 300 feet away
- Lightweight and portable for hard-to-access areas
- Simple setup, no equipment modification required
- Quick installation and removal from gear
- Adjustable travel and locators to accommodate entire product line
- Reduces or eliminates need for arc-flash hazard suits
- Eliminates all hazardous manual contact with gear during operation
- Designed, manufactured, and assembled in the USA

