

## DAB+ / FM & DIGITAL TV RECEIVER

### HDR1



- ✓ Fully compliant with DMB-TH & DAB+ standard
- ✓ DAB/DAB+: Slide Show and Extended EPG
- ✓ USB PVR-Ready Support
- ✓ Display EPG / Subtitle
- ✓ Low power consumption
- ✓ Internet Radio
- ✓ Weather Forecast
- ✓ Media Player (Support MP3, JPG, AVI)
- ✓ FM Radio
- ✓ 18 months Warranty
- ✓ Network-shared File Play  
(ONLY AVAILABLE FOR WINDOWS XP)

#### HDR1 Specification

|                |                     |                                           |
|----------------|---------------------|-------------------------------------------|
| TV Tuner       | RF input            | 110-862 MHz                               |
|                | Loop through output | 110-862 MHz                               |
|                | Signal Decoding     | Standard                                  |
| Video Decoding | Bandwidth           | DMB-TH (GB20600-2006)                     |
|                | Standard            | 8M                                        |
|                | Display ratio       | Support MPEG1, 2 MP@HL/ML H.264 HD / SD   |
| Audio Decoding | Aspect ratio        | 1080p / 1080i / 720p / 576p / 576i        |
|                | Standard            | 4:3 (Letterbox), 16:9 (Letterbox, full)   |
|                | Audio format        | ISO / IEC 11172-3                         |
| DAB / FM Tuner | Audio Output        | Support MPEG1, 2 layer I and II, AC3, AAC |
|                | Sampling frequency  | SPDIF                                     |
|                | RF input            | 32, 44.1, 48, 96KHz                       |
| HD Output      | DAB Decoding        | 87.5-108MHz (FM) 175-239.2 MHz (DAB)      |
|                | Format              | HE-AAC / AAC+                             |
|                | Connector           | 1080p / 1080i / 720p                      |
| Front Panel    | Function Key        | HDMI / YPbPr                              |
|                | Display             | 7 Keys                                    |
|                | USB 2.0             | 4 Digit LED                               |
| Back Panel     | TV Tuner            | 1                                         |
|                | Tuner Loop Through  | 1                                         |
|                | CVBS                | 1                                         |
| Power Supply   | Y/Pb/Pr             | 1                                         |
|                | HDMI                | 1                                         |
|                | Stereo Audio        | 1                                         |
| Others         | Optical             | 1                                         |
|                | Coaxial             | 1                                         |
|                | Ethernet (RJ45)     | 1                                         |
| Power Supply   | USB 2.0             | 1                                         |
|                | Radio Tuner         | 1                                         |
|                | Input Voltage       | AC100-240V, 50/60Hz                       |
| Others         | Power Consumption   | Max 15W, Stand by 1W                      |
|                | Working temperature | 0-45°C                                    |
|                | Size                | 280mm (W) x 202mm (D) x 43mm (H)          |
|                | Weight              | 0.85Kg                                    |